

## Allure



Design iGuzzini

iGuzzini

Last information update: March 2025

### Product configuration: SA53+X799.01+X805.01

SA53: Wall-mounted luminaire - Neutral White - Integrated power supply - Casambi Bluetooth - AS (Up) optic + AS (Down) optic  
X799.01: Flush-mounted polycarbonate guard - for Allure 120x150 - White  
X805.01: Spacer base for installation via conduit - for Allure 120x150 - White



### Product code

SA53: Wall-mounted luminaire - Neutral White - Integrated power supply - Casambi Bluetooth - AS (Up) optic + AS (Down) optic

### Technical description

Wall-mounted luminaire with Neutral White LED lamps - AS (Up) optic + AS (Down) optic. Consists of an optical assembly, a top glass, a bottom glass and a cover raster to be purchased separately. The optical assembly is made of an aluminium alloy, subjected to a multi-step, pre-treatment process in which the main phases are degreasing, fluorozirconation (a protective surface film) and sealing (with a nano-structured silane layer). The following painting stage consists of a primer and a liquid acrylic paint, cured at 150°C, with a high level of weather and UV ray resistance. The tempered sodium-calcium upper cover glass has black serigraphy on the edge and is 5mm thick. The tempered sodium-calcium lower cover glass has black serigraphy on the edge and is 4mm thick. The product is supplied with an aluminium optic in a set back position for the lower optical assembly to obtain maximum visual comfort and a flush-mounted aluminium optic for the upper optical assembly to obtain maximum efficiency. Fitted with a PG13.5 cable gland for 8.5mm to 12.5mm diameter cables. Luminaire with Bluetooth Low Energy technology (Casambi). Frequency 2.4 GHz. The luminaire can be controlled with the Casambi system app and components that enable on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via an app (iBeacon) that enables smart functions for third party applications. All external screws used are made of A2 stainless steel.

### Installation

Max luminaire-luminaire distance (\*): 10m; max smartphone-luminaire distance (\*): 10m.

### Colour

White (01) | Black (04) | Green (07) | Grey (15) | Rust Brown (F5)

### Weight (Kg)

1.66

### Mounting

wall surface

### Notes

The raster (whether flush-mounted, with a visible border or a PMMA screen) must be fitted and can be purchased separately. (\*In all case, the maximum distance is affected by the presence of physical obstacles, like concrete, brick or metal panel walls.) We suggest that a test is conducted at the installation site.

Complies with EN60598-1 and pertinent regulations



IK06

IP66



### Accessory code

X799.01: Flush-mounted polycarbonate guard - for Allure 120x150 - White

### Technical description

Polycarbonate guard to be installed in the lower part of the Allure product. The guard is flush-mounted using two stainless steel screws. Coated with two-component liquid paint (catalyst+ enamel).

### Installation

The product is installed using two stainless steel screws.


### Colour

White (01)

### Weight (Kg)

0.03

Complies with EN60598-1 and pertinent regulations



### Accessory code

X805.01: Spacer base for installation via conduit - for Allure 120x150 - White

### Technical description

Die-cast aluminium spacer base designed for installing the Allure product via conduit tubes. The base is fitted with 4 holes (one on each side of the accessory). The accessory code includes 3 rubber stoppers for the holes that are not used during installation.


### Colour

White (01)

### Weight (Kg)

0.27

Complies with EN60598-1 and pertinent regulations



#### Technical data

Im system:	1513	Life Time LED 2:	100,000h - L80 - B10 (Ta 40°C)
W system:	13	Lamp code:	LED
Im source:	2310	Number of lamps for optical assembly:	1
W source:	11	ZVEI Code:	LED
Luminous efficiency (Im/W, real value):	116.4	Number of optical assemblies:	1
Im in emergency mode:	-	Intervallo temperatura ambiente:	from -30°C to 50°C.
Total light flux at or above an angle of 90° [Lm]:	796	Power factor:	See installation instructions
Light Output Ratio (L.O.R.) [%]:	66	Inrush current:	20 A / 25 µs
CRI (minimum):	80	Maximum number of luminaires of this type per miniature circuit breaker:	B10A: 81 luminaires B16A: 130 luminaires C10A: 135 luminaires C16A: 221 luminaires
Colour temperature [K]:	4000	Overvoltage protection:	2kV Common mode & 1kV Differential mode
MacAdam Step:	3	Control:	Casambi
Life Time LED 1:	100,000h - L80 - B10 (Ta 25°C)		

#### Polar

