Design iGuzzini

iGuzzini

Last information update: September 2025

Product configuration: SA42.01+X799.01

SA42.01: Wall-mounted luminaire - Warm White - Integrated power supply - Casambi Bluetooth - AF (Down) optic - 7.1W 577.2lm - 2700K - White

X799.01: Flush-mounted polycarbonate guard - for Allure 120x150 - White



153 96

Product code

SA42.01: Wall-mounted luminaire - Warm White - Integrated power supply - Casambi Bluetooth - AF (Down) optic - 7.1W 577.2Im - 2700K - White

Technical description

Wall-mounted luminaire with Warm White LED lamps, AF (Down) optic Consists of an optical assembly, a top glass, a bottom glass and a cover raster to be purchased separately. The optical assembly is made of an aluminium alloy, subjected to a multi-step, pretreatment process in which the main phases are degreasing, fluorozirconation (a protective surface film) and sealing (with a nanostructured silane layer). The following painting stage consists of a primer and a liquid acrylic paint, cured at 150°C, with a high level of weather and UV ray resistance. The tempered sodium-calcium upper cover glass has black serigraphy on the edge and is 5mm thick. The tempered sodium-calcium lower cover glass has black serigraphy on the edge and is 4mm thick. The product is supplied with an aluminium optic in a set back position for the lower optical assembly to obtain maximum visual comfort and a flush-mounted aluminium optic for the upper optical assembly to obtain maximum efficiency. Fitted with a PG13.5 cable gland for 8.5mm to 12.5mm diameter cables. Luminaire with Bluetooth Low Energy technology (Casambi). Frequency 2.4 GHz. The luminaire can be controlled with the Casambi system app and components that enable on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via an app (iBeacon) that enables smart functions for third party applications. All external screws used are made of A2 stainless steel.

Installation

Max luminaire-luminaire distance (*): 10m; max smartphone-luminaire distance (*): 10m.

 Colour
 Weight (Kg)

 White (01)
 1.66

Mounting

wall surface

Notes

The raster (whether flush-mounted, with a visible border or a PMMA screen) must be fitted and can be purchased separately. (*In all case, the maximum distance is affected by the presence of physical obstacles, like concrete, brick or metal panel walls.) We suggest that a test is conducted at the installation site.

Complies with EN60598-1 and pertinent regulations



IK06















Accessory code

X799.01: Flush-mounted polycarbonate guard - for Allure 120x150 - White

Technical description

Polycarbonate guard to be installed in the lower part of the Allure product. The guard is flush-mounted using two stainless steel screws. Coated with two-component liquid paint (catalyst+ enamel).

Installation

The product is installed using two stainless steel screws.

 Colour
 Weight (Kg)

 White (01)
 0.03

Complies with EN60598-1 and pertinent regulations

Technical data			
Im system:	801	Life Time LED 1:	100,000h - L80 - B10 (Ta 25°C)
W system:	7.1	Life Time LED 2:	100,000h - L80 - B10 (Ta 40°C)
Im source:	1040	Lamp code:	LED
W source:	5.5	Number of lamps for optical	1
Luminous efficiency (lm/W,	112.8	assembly:	
real value):		ZVEI Code:	LED
Im in emergency mode:	-	Number of optical	1
Total light flux at or above an angle of 90° [Lm]:	0	assemblies:	
		Intervallo temperatura	from -30°C to 50°C.
Light Output Ratio (L.O.R.) [%]:	77	ambiente:	
		Power factor:	See installation instructions
CRI (minimum):	80	Inrush current:	20 A / 25 μs
Rf (Colour Fidelity Index):	86	Maximum number of	
Rg (Gamut Index):	96	luminaires of this type per miniature circuit breaker:	B10A: 81 luminaires B16A: 130 luminaires C10A: 135 luminaires C16A: 221 luminaires
Colour temperature [K]:	2700		
MacAdam Step:	3		
		Overvoltage protection:	2kV Common mode & 1kV
		Overvoltage protection:	Differential mode
		Control:	Casambi



