



Last information update: August 2023

**Product code**MU36: Wall-mounted emergency indication luminaire - LED - Centralized Testing **Attention! Code no longer in production****Technical description**

Luminaire with LED lamp for indicating escape routes. Wall-mounted in a parallel position. White finish, shaped sheet steel component holder structure. Permanent operation (always on - SA); in event of blackouts guarantees an emergency autonomy of 3 hours with the battery fully charged. Sign visible from a distance of 25m (in compliance with UNI EN 1838). Luminaires with centralized testing are equipped with an interface circuit that can interact with an external accessory control unit (code no. MXS9). In the event of a fault or malfunctioning the devices involved are indicated on the control unit display by means of a specific identification number. LED warning lamp with function that indicates which devices are operating correctly and if there are any faults. For explanations of all the operating warning lamp functions, see the instructions sheet. Ni-Cd battery with 24 hour recharge time. Indicator screens available with a separate code (pictogram design L22).

Installation

Wall-mounted - by removing the cover safety guard and fixing the structure to the surface using screws and screw anchors (not supplied).

Colour

White (01)

Mounting

wall surface

Wiring

Inside the structure - the protection panel must be removed and the necessary connections made on the standard terminals.

Notes

Inhibition Mode Function (only for versions with centralized testing): allows the system to be switched off even for long periods. The emergency system must be reactivated using the control unit code no. MXS9.

Complies with EN60598-1 and pertinent regulations

**Technical data**

Im system:	35 (*)	CRI:	80
W system:	1 (*)	Colour temperature [K]:	4000
Im source:	35 (*)	Number of lamps for optical assembly:	1
W source:	1 (*)	ZVEI Code:	LED
Luminous efficiency (Im/W, real value):	35.0 (*)	Number of optical assemblies:	1
Im in emergency mode:	-		