

Project name: \_\_\_\_\_

Type: \_\_\_\_\_



Direct light luminaire that offers a vast range of accessories for guaranteeing extremely flexible, effective lighting, avoiding unwanted glare and reducing light pollution.

**Luminaire characteristics:**

**Power input:** 19W

**Lumens:** 950 to 1290 lm

**Luminaire efficacy:** 50 to 67lm/W

**Source:** White LED (LM-80 tested)

3000K: 80CRI,

4000K: 80CRI.

**Lumen maintenance:** LM-79 tested

80% of initial lumens at 66 000 hours - L80 (Ta25C)

80% of initial lumens at 100 000 hours - L80 (Ta40C)

**Optics:** Available in spot or flood beam.

**Mounting:** Surface mounted, installs on a standard 4" Junction box.

**Material:**

Body: Die-cast aluminum.

Reflector: Anodized aluminum.

Diffuser: Tempered glass.

Hardware: Stainless steel screws and silicone gasket.

**Electrical:** Universal high efficiency electronic power supply, rated at 50 000 hours, 120 - 277V.


**Finish:** Gray (RAL9007) or White (RAL9016) painted finish with a high level of weather and UV resistance. The semi-gloss finish coating is electrostatically applied, durable acrylic enamel baked at high temperatures for superior color retentive finish.

**Weight:** 8.6lbs (3.90kg).


**Warranty:** 5 year limited warranty.

**Certification:** cULus listed for wet location.

**Ratings:** IP66, IK07



**FRONT VIEW**



**SIDE VIEW**



Project name: \_\_\_\_\_

Type: \_\_\_\_\_

**PHOTOMETRIC DATA**

Visit [iguzzini.com/us](http://iguzzini.com/us) for complete photometric data.







LOAD (W)	CCT (K)	CRI	OPTIC	LUMENS (lm)	EFFICACY (lm / w)	MAX CANDELA (cd)	MODELS
19W	4000K	80	SPOT	1290	67	20405	I.BD46
	3000K			1100	57	17420	I.BD47
	4000K		FLOOD	1110	58	3190	I.BD48
	3000K			950	50	2725	I.BD49



Project name: \_\_\_\_\_



Type: \_\_\_\_\_

**ACCESSORIES (TO BE ORDERED SEPARATELY)**

- |                       |                    |                                   |   |
|-----------------------|--------------------|-----------------------------------|---|
| <input type="radio"/> | <b>I.BZ63 - 01</b> | Accessory frame (white)           |  |
| <input type="radio"/> | <b>I.BZ63 - 15</b> | Accessory frame (gray)            |   |
| <hr/>                 |                    |                                   |   |
| <input type="radio"/> | <b>I.BZ67 - 24</b> | Elliptical lens (transparent)     |  |
| <hr/>                 |                    |                                   |   |
| <input type="radio"/> | <b>I.BZ66 - 24</b> | Prismatic glass (transparent)     |  |
| <hr/>                 |                    |                                   |   |
| <input type="radio"/> | <b>I.BZ71 - 13</b> | Protection grid (stainless steel) |  |
| <hr/>                 |                    |                                   |   |
| <input type="radio"/> | <b>I.BZ73 - 02</b> | Direction flap (black)            |  |
| <hr/>                 |                    |                                   |   |
| <input type="radio"/> | <b>I.BZ74 - 02</b> | Visor (black)                     |  |

**\*I.BZ63 is required for all accessories except for I.BZ74.**

**MOUNTING (TO BE ORDERED SEPARATELY)**

- |                       |                    |                               |   |
|-----------------------|--------------------|-------------------------------|---|
| <input type="radio"/> | <b>I.BZ76</b>      | L-shaped bracket for cornices |  |
| <hr/>                 |                    |                               |   |
| <input type="radio"/> | <b>I.BZI9 - 01</b> | Wall-mounted base (white)     |  |
| <input type="radio"/> | <b>I.BZI9 - 15</b> | Wall-mounted base (gray)      |   |

**ORDERING INFO**

MODEL	VOLTAGE	FINISH
<input type="radio"/> <b>I.BD46</b> - 4000K, Spot <input type="radio"/> <b>I.BD47</b> - 3000K, Spot <input type="radio"/> <b>I.BD48</b> - 4000K, Flood <input type="radio"/> <b>I.BD49</b> - 3000K, Flood	<input type="radio"/> <b>UNV</b> - 120-277V	<input type="radio"/> <b>01</b> - White <input type="radio"/> <b>15</b> - Gray

DUE TO CONTINUOUS IMPROVEMENTS, THE INFORMATION HEREIN MAY BE CHANGED WITHOUT NOTICE.

LAST UPDATE: JULY 17, 2018

JP - R3