

DALI IP20 10/17W constant current power supply - for 2 Crystal HO Tunable White recessed luminaires

Design iGuzzini

iGuzzini

Last information update: January 2025



Accessory code

PD84: DALI IP20 10/17W constant current power supply - for 2 Crystal HO Tunable White recessed luminaires

Technical description

DALI 10/17 W dimmable constant current electronic power supply.

Can be used for HO Tunable White models.

Input Vin=220÷240 Vac 50÷60Hz.

SELV output.

The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

Installation

Compatible with opening for Crystal recessed fitting assembly.

Colour

Indeterminate (00)

Weight (Kg)

0.23

Dimension (mm) (*)

166x51x29.2

* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.

Cable clamp on primary and secondary.

Notes

DT8 type DALI check. 1 address, 1 DALI load (2 mA).

Complies with EN60598-1 and pertinent regulations



IP20



Technical data

Frequency [Hz]: 0/50/60

Current out [mA]: 600

Inrush current: 29 A / 153 µs

Maximum number of LED power supply units of this type per miniature circuit breaker:

B10A: 32 power supply units

B16A: 51 power supply units

C10A: 53 power supply units

C16A: 86 power supply units

Minimum dimming %: 1

Overvoltage protection: 2kV Common mode & 1kV Differential mode

Control: DALI-2